

37MM, THREE-PHASE COMMERCIAL METER STACK MODULES

- ✓ Each socket is a 7 terminal block with lever bypass and jaw release.
- ✓ Ringless covers.
- ✓ Provision for 3-pole main tenant breakers (circuit breakers not included).
- ✓ Indoor/outdoor construction.
- ✓ Main tenant breakers can exit top, bottom, or back.
- ✓ If being used in outdoor application and exiting the top, mount Myer type hubs on rainproof cap.
- ✓ Short circuit ratings up to 100 ampere rms symmetrical depending upon the kAIC rating of installed main tenant circuit breakers and main device.
- ✓ Copper horizontal bus supplied as standard.
- ✓ Non-EUSERC areas.

TABLE 4-25. 37MM — THREE-PHASE COMMERCIAL METER STACK MODULES

System Voltage	Ampere Rating Per Meter Socket	Number of Meter Sockets	Bus Ampacity	Number of Jaws Per Meter Socket ^①	Main Tenant Breaker Type	Catalog Number	UPC Code	
208Y/120 volt, 3-phase, 4-wire 240/120 volt, 3-phase, 4-wire Delta (B-Phase is high leg)	225	1	1200	7	Bolt-on Type	37MM120R12 ^③	786849052881	
		2	1200	7	EHD3_ ^②	37MM220R12 ^③	786849052898	
		3	1200	7	CC3_X	37MM320R12 ^③	786849052904	
		4	1200	7	CHH3_H2X	37MM420R12 ^③	786849052911	
	400	1	1200	7	CHH3_H4X CHH3_	37MM140R12 ^④	786849052928	
		400	1	1200	7	400 Ampere K-Frame Included	37MM140R1240 ^⑤	782114754450
							37MM140HR1240 ^⑥	782113935379
		400	2	1200	7	400 Ampere K-Frame Included	37MM240R1240	782116107865
		400 Continuous	1	1200	7	400 Ampere L-Frame Included	37MM140R1240K ^⑦	782116303847
		400 Continuous	1	1200	7	400 Ampere L-Frame Included	37MM140HR1240K ^⑧	782116303854

^① If a socket in a 37MM meter stack module needs to be single-phase, order **37MM1CK**. This will convert the 3-phase socket to single-phase.

^② EHD main tenant breakers require one **37MMCBK** kit per breaker.

^③ Add NJ suffix for New Jersey "NJUA" approved units.

^④ 320 ampere continuous rated socket with provisions for two main tenant breakers.

^⑤ Unit is bottom exit only.

^⑥ Rated at 100 kAIC.

^⑦ Rated at 25 kAIC.

^⑧ Rated at 35 kAIC.

