



Shown actual size:
Maestro dimmers
and 2-gang Claro
wallplate in White (WH).

Product family features

- Can be used in conjunction with the following dimmer(s) and switch(es): Maestro®, Maestro IR®, Maestro Wireless®, Pico® wireless control, Diva®, Skylark Contour®, Skylark®
- All Lutron wallplates are screwless, seamless, and have no visible hardware; the front plate securely snaps into the alignment adapter plate
- Full line of wiring devices in Designer style opening
- Blank inserts available for Gloss colors (DV-BI-) and Satin Colors® (SC-BI-)
- Customize your designer wallplate with engraving. Contact customer service to get started; 1.888.LUTRON1

Ganging and derating

- Designer wallplates use standard ganging
- Requires fins to be removed from dimmers for proper spacing (“Fins Broken” ganging), see pg. 179
- May require derating (i.e., reduction of dimmer capacity due to fin removal), see Derating Tables, pg. 179

Receptacles for dimming use (tamper resistant)



- Duplex for dimming both connected loads
- Projecting nubs prevent standard plugs from being used
- Requires replacement plug for dimming table and floor lamps
- Includes 1-gang wallplate
- Tamper resistant shutter mechanism

Dual dimming tamper resistant*

15 A	120/125 V	NTR-15-DDTR- XX ¹
20 A	120/125 V	NTR-20-DDTR- XX ¹

Receptacles for half dimming use (tamper resistant)



- Top half for dimming
- Projecting nub prevents standard plug from being used
- Requires replacement plug for dimming table and floor lamps
- Bottom half is a general use receptacle and will fit standard duplex plugs
- Includes 1-gang wallplate
- Tamper resistant shutter mechanism

Half dimming tamper resistant*

15 A	120/125 V	NTR-15-HDTR- XX ¹
20 A	120/125 V	NTR-20-HDTR- XX ¹

Replacement plugs for dimming (use with receptacles at left)



- This plug required for use with Lutron receptacles for dimming use—plug will work in standard receptacle
- Easily replaces the existing plugs on lamps

Replacement plugs

120/125 V	RP-FDU-10-WH
White	
120/125 V	RP-FDU-10-BR
Brown	

UL/CSA/NOM regulatory approvals

Important application notes:

- Receptacles and plugs for dimming use are UL listed for use with all Lutron wallbox dimmers included in this catalog.
- If there is only one electrical feed to the receptacle, then the duplex DFDU must be used.
- If the hot and dimmed hot feeds to the split duplex HFDU are supplied from different circuits or split-wired, with separate switch-legs, a means to simultaneously disconnect these circuits must be provided at the panel board where they originate (NEC 210.7(C) 2002 Edition). A 2-pole circuit breaker or two single-pole circuit breakers with an approved handle tie can be used to accomplish this simultaneous disconnect. Feed-through dimming panels, which are those without breakers, are recommended when using the HFDU.
- For detailed information, see Application Notes #91 (Guide to Dimming Table Lamps) and #109 (Guide to Dimming Portable Lamps via Receptacles) at www.lutron.com/applicationnotes.

XX¹: Architectural matte color codes, see pg. 162 (1-gang wallplate included)

*Metal finishes are only available as separate wallplates. Match with separate Black (BL) controls and accessories.