

Table 11. NX Clip-Style Current-Limiting Fuse (Refer to Figure 2) Rating*

Voltage (kV)	Continuous Current (A)	Mounting Code Number	Fuse Diameter (in.)	Catalog Number
4.3	18	4	1.125	FA1H18
	25	4	1.125	FA1H25
	35	4	1.125	FA1H35
	45	4	2	FA1H45
	50	4	2	FA1H50
	65	4	2	FA1H65
	75	4	2	FA1H75
	105	4	2	FA1H100
5.5	6	4	1.125	FA2H6
	8	4	1.125	FA2H8
	10	4	1.125	FA2H10
	12	4	1.125	FA2H12
	18	4	1.125	FA2H18
	20	4	2	FA2H20
	25	4	2	FA2H25
	30	4	2	FA2H30
	40	4	2	FA2H40
	50	4	2	FA2H50
65	4	2	FA2H65	
75	4	2	FA2H75	
8.3	1.5	4	1.125	FA3H1
	3	4	1.125	FA3H3
	4.5	4	1.125	FA3H4
	6	4	1.125	FA3H6
	8	4	1.125	FA3H8
	10	4	1.125	FA3H10
	12	4	1.125	FA3H12
	18	4	2	FA3H18
	20	4	2	FA3H20
	25	4	2	FA3H25
	30	4	2	FA3H30
	40	4	2	FA3H40
	50	5	3.438	FA3H50
	65	5	3.438	FA3H65
80	5	3.438	FA3H80	
100	5	3.438	FA3H100	
15.5	1.5	5	1.125	FA4H1
	3	5	1.125	FA4H3
	4.5	5	1.125	FA4H4
	6	5	2	FA4H6
	8	5	2	FA4H8
	10	5	2	FA4H10
	12	5	2	FA4H12
	18	5	2	FA4H18
	20	5	2	FA4H20
	25	5	2	FA4H25
	30	5	2	FA4H30
	40	5	2	FA4H40
	50	6	3.438	FA4H50
	65	6	3.438	FA4H65
	80	6	3.438	FA4H80
	100	6	3.438	FA4H100†

Table 11. NX Clip-Style Current-Limiting Fuse (Refer to Figure 2) continued Rating*

Voltage (kV)	Continuous Current (A)	Mounting Code Number	Fuse Diameter (in.)	Catalog Number
23	6	6	2	FA5H6
	8	6	2	FA5H8
	10	6	2	FA5H10
	12	6	2	FA5H12
	18	6	2	FA5H18
	20	6	2	FA5H20
	25	6	2	FA5H25
	30	6	2	FA5H30
	40	6	2	FA5H40
	27	6	9	3.438
8		9	3.438	FA9H8
10		9	3.438	FA9H10
12		9	3.438	FA9H12
15		9	3.188	FA9H15
18		9	3.438	FA9H18
20		9	3.438	FA9H20
25		9	3.438	FA9H25
30		9	3.438	FA9H30
40		9	3.438	FA9H40
50	9	3.438	FA9H50	
38	6	10	3.438	FA10H6
	8	10	3.438	FA10H8
	10	10	3.438	FA10H10
	12	10	3.438	FA10H12
	15	10	3.438	FA10H15
	18	10	3.438	FA10H18
	20	10	3.438	FA10H20
	25	10	3.438	FA10H25
	30	10	3.438	FA10H30
	40	10	3.438	FA10H40
50	10	3.438	FA10H50	

* 4.3, 5.5, 8.3, 15.5, 23 kV have 50,000 A symmetrical rating, 27 and 38 kV have 35,000 A symmetrical rating.

** Code number of mounting must match code number of fuse or switchblade.

Note: Fuse extenders available as follows:

Catalog Number FEXT45 adapts Code 4 fuses to Code 5 mountings

Catalog Number FEXT56 adapts Code 5 fuses to code 6 mountings