



designed to be better.

[Search](#)

Non-Fusible Safety Switch

PS30SSAX

Non-Fusible Safety Switch with Auxillary Contact. 30 amp, 600 vac.

[Submit Query](#)

Where to buy

[Submit Query](#)

0

[Email](#) [Print](#)



Representative image shown.

- [SPECIFICATIONS](#)
- [RESOURCES](#)

features & benefits

- Top, Bottom, or back feed.
- Units are shipped without holes for conduit.
- Spot drills for locating hole saw or knockouts are provided for top, bottom, or back feed.
- End user decides at installation whether top, bottom, or back feed is appropriate.
- No closure plug kits required.
- Units are not provided with conduit hubs.

Top 5 Resources

- [Commercial & Industrial Products \(Brochure\)](#)
- [Disconnect Switch 30,60,100 Amp Outdoor/indoor \(Instruction Sheet No.\)](#)

specifications

General Info

- Type: Non-Fusible Safety Switch w/Auxiliary

Listing Agencies/Third Party Information

- CSA Listing Info: No
- CUL Listing No: No
- cU Lus: Yes
- cU Rus: No
- Federal Spec: No
- UL Listing No: No
- U N SPS C: 39121403
- U R: No

Technical Information

- Amps: 30 Amp
- Category Rating: Non-Fusible Safety Switches
- Volts: 600VAC
- Volts A C: 600

Buy American Act Compliance

- Country of Origin: UNITED STATES OF AMERICA
- Buy American Act Status: Buy American Act Compliant
-



resources BROCHURE

 Commercial & Industrial ProductsPDF (3.52mb)

INSTRUCTION SHEET NO.

 Disconnect Switch 30,60,100 Amp Outdoor/indoorPDF (161.97kb)