

Buzzers

Strap-Mounted

660 Series



Edwards 660 Series buzzers and bells are compact, strap-mounted devices designed for flush mounting in standard electrical boxes. They require a 598 transformer and push button.

Features and Specifications

- Easy flush mounting
- Cover with a single receptacle outlet cover plate (user supplied)

Ordering Information

Description	Cat. No.	Operating Voltage	Current ¹	VA	dB at 1m/10ft.	DC Coil Res (Ohms)
Ringcall™ Bell	660	8-10V AC	1.5 A	15	90/80	4.75
Buzacall™ Buzzer	661	8-10V AC	1.3 A	13	90/80	6
Tucall™ Bell/Buzzer	662	8-10V AC	1.5 A	15	90/80	4.75

¹Ratings at 10V AC

Weights and Dimensions

Cat. No.	Approx. Net Weight (lb.)	Approx. Shipping Weight (lb.)	Depth
			A
660	0.30	0.32	1 3/8" (35mm)
661	0.30	0.32	7/8" (22mm)
662	0.30	0.32	1 3/8" (35mm)

